



CinHELL

BLUE

BT-BC 150 Battery Charger

Art.-No. 10.891.22

Powerful and mobile workshop charger for 12 V and 24 V charging voltage and jump start feature. Ideal for workshops and farmers. Charging capacity can be regulated with 5 settings and the charger is thus also suitable for batteries with a lower capacity. The integrated smoothing inductor reduces the residual ripple from the rectify charging voltage. It preserves the battery which will be load and extends compared with rough charging voltage the durability of the battery. The jump start feature (150A/2s) can be activated with a remote cable (3 metre) by pressing a rocker switch. The large gauge shows the current charging rate and the charging voltage. The fully insulated pole clamps warrant a perfect connection to battery poles. The unit is equipped with triple reverse voltage protection and overload protection. The housing is made of scratch-resistant, powder coated sheet steel housing with a push bar.

Features

- Construction protection class I
- Sheet steel housing (1)
- Charging voltage indicator (voltmeter) (2) and charging current indicator (ampere meter) (3)
- Push bar (4)
- Charging voltage switch (0 V / 12 V / 24 V) (5)
- Charging rate switch (5-position) (6)
- 3 steps overload- and reverse voltage protection (overload switch (7), strip fuse (8), thermal protection for transformer)
- Integrated cable storage (9)
- 3 m remote cable with push-button (10)
- 2 m mains cable with safety plug
- 2 m charging cable (6 mm²) with fully insulated pole clamps (11)
- Rubber feet (12)
- Wheels (13)

Technical data

- Mains: 230 V ~ 50 Hz
- Charging capacity: 12 V = 0.8 – 25 A arith. / 1.2 – 35 A eff.
24 V = 1.6 – 17 A arith. / 2.7 – 23 A eff.
- Jump start feature: 150 A (2 sec)
- For lead batteries: min. 3 Ah up to max. 400 Ah
- Net weight: 14.8 kg
- Gross weight: 16 kg
- Packing dimensions: 320 x 260 x 510 mm
- Bar code: 4006825562378
- Sales unit: 1 pc

