





## BT-PG 2000/3 **Power Generator**

Art.-No. 41.524.30

This "power station" supplies energy and provides security.

Power will be available whenever it is needed. Power failures or insufficient current supply are no longer a problem; whether during camping, at building sites, in homes or cottages, on boats or in the garden. This equipment can be used nearly everywhere, and, with its continuous power supply of 2,000 watts provides sufficient power for many applications. The large 13-litre tank ensures continuous operation for 11 hours at 2/3 load. The power generator is powered by a highquality 4-stroke engine and is equipped with an overload switch.

## **Features**

- Large 13-litre tank for continuous power (1)
- Convenient fuel gauge (2)
- 2 x 230 V socket for simple current drain (3)
- Overload switch for equipment reliability (4)
- Practical voltmeter (5)
- Powerful 4-stroke drive motor (6)
- Linkage to start the motor (7)
- Oil deficiency safety device to protect the motor
- Full crank shaft
- Automatic voltage regulation

## **Technical Data**

Generator: Synchronous Continuous Power (S1): 1 x 2,000 W Max. Power (S2 2 min): 1 x 2,200 W Nominal current: 2 x 230 V ~

Frequency: 50 Hz

1 cylinder, 4-stroke air cooled Type:


Cylinder capacity: 196 cm<sup>3</sup> Max. motor power: 4 **kW** / 5.4 HP

Fuel: Petrol Tank capacity: 13 I

Running time at 2/3 load: approx. 11 hours

Noise level: 95 dB (A) Product weight: 36.4 kg

## **Logistic Data**



Packing dimensions: 620 x 470 x 475 mm Bar code: 4006825 575606

Sales unit: 1 pc

