





BT-PG 2000/1 Power Generator


Art.-No. 41.523.77

This "power station" supplies energy and provides security.

Power will be available whenever it is needed. Power failures or insufficient current supply are no longer a problem; whether during camping, at building sites, in homes or cottages, on boats or in the garden. This equipment can be used nearly everywhere, and, with its continuous power supply of 2,000 watts provides sufficient power for many applications. The large 15-litre tank ensures continuous operation for 14 hours at 2/3 load. The power generator is powered by a high-quality 4-stroke engine and is equipped with an overload switch.

Features

- Large 15-litre tank for continuous power (1)
- Convenient fuel gauge (2)
- 2 x 230 V socket for simple current drain (3)
- Overload switch for equipment reliability (4)
- Practical voltmeter (5)
- Powerful 4-stroke drive motor (6)
- Linkage to start the motor (7)
- Oil deficiency safety device to protect the motor
- Full crank shaft
- Automatic voltage regulation





Technical Data

Generator: Synchronous
Continuous Power (S1): 1 x 2,000 W
Max. Power (S2 2 min): 1 x 2,200 W
Nominal current: 2 x 230 V / 1 ~

Frequency: 50 Hz

Type: 1 cylinder, 4-stroke air cooled

Cylinder capacity: 196 cm³
 Max. motor power: 3.74 kW / 5 HP

Fuel: PetrolTank capacity: 15 l

Running time at 2/3 load: approx. 14 hours
Noise level: 94 dB (A)
Net weight: 39.1 kg
Gross weight: 41.0 kg

Packing dimensions: 635 x 470 x 485 mm
 Bar code: 4006825 568325

Sales unit: 1 pc

