





KCST 1000 D Power Generator

Art.-No. 41.512.51

Features

- Inverter technology to operate with sensitive equipment for example PC, TV...
- Powerful 4-stroke drive engine
- Large 2.7-litre tank with lockable tank ventilation (1) for continuous operation
- Carrying handle for easy transport (2)
- Stable supporting stand (3)
- Safety tripping element for equipment protection (4)
- Econ-switch for quiet and sparing working (5)
- 1x 230 V socket for easy current drain (6)
- 1x 12 V connection (7) with adapter cable (7) for cigarette lighter plug
- Integrated fuel tap (8)
- Reversing starter to start the machine (9)

Technical Data

Generator: Digital Inverter

Continuous power (230 V): 900 W

Max. Power (230 V): 1,000 W (S2 5 min)

Power connection (12 V d. c.): 60 W

Rated voltage: 230 V ~ / 12 V d. c.
 Rated current: 3.9 A ~ / 5 A (12 V d. c.)

■ Frequency: 50 Hz

■ Type: 1 cylinder, 4 stroke air cooled

Displacement: 53 cm³

Max. Power: 1.2 kW / 1.6 HPFuel: Petrol lead-free

Tank capacity: 2.7 I

Consumption at 2/3 load: approx. 0.45 l/h

Protection type: IP 23
Spark plug: A5RTC
Net weight: 13.7 kg
Gross weight: 16.0 kg

Packing dimensions: 510 x 290 x 450 mm

