Service information

We have competent service partners in all countries named on the guarantee certificate whose contact details can also be found on the guarantee certificate. These partners will help you with all service requests such as repairs, spare and wearing part orders or the purchase of consumables. Please note that the following parts of this product are subject to normal or natural wear and that the following parts are therefore also required for use as consumables.

Category	Example
Wear parts*	Rubber Gasket, Belt, Rubber Washer, Mixing Blades
Consumables*	
Missing parts	

^{*} Not necessarily included in the scope of delivery!

In the effect of defects or faults, please register the problem on the internet at www.isc-gmbh.info. Please ensure that you provide a precise description of the problem and answer the following questions in all cases:

- Did the equipment work at all or was it defective from the beginning?
- Did you notice anything (symptom or defect) prior to the failure?
- What malfunction does the equipment have in your opinion (main symptom)?
 Describe this malfunction.


Declaration of confirmity

explains the following confor the following product	mity according to EU directive	es and norms for	
Cement Mixer CMX-125U (Ozito)			
□ 2014/29/EU □ 2005/32/EC_2009/125/EC □ 2014/35/EU □ 2006/28/EC ※ 2014/30/EU □ 2014/32/EU □ 2014/53/EC □ 2014/68/EU □ 90/396/EC_2009/142/EC □ 89/686/EC_96/58/EC ※ 2011/65/EU	P = 0,55 KW; L/Ø = cm Notified Body: TÜV SÜD Prod	r (A); guaranteed L _{wa} = 96 dB (A) duct Service GmbH (0036) 5, 90339 München	
	rd references: EN 60204-1; 014-1; EN 55014-2; EN 6100	, ,	
Landau/Isar, den 06.07.2016	Weichselgartner/General-Manager	Mayr/Product-Management	
First CE: 16 ArtNo.: 44.722.91		Archive-File/Record: NAPR014361 Documents registrar: R. Gehard Wiesenweg 22, D-94405 Landau/Isar	



CMX-125U

GB Additional operating & safety instructions Cement Mixer







Danger! Read the operating instructions to reduce the risk of inquiry.



Beware of electrical voltage!



Caution! Wear ear-muffs. The impact of noise can cause damage to hearing.



Caution! Wear a breathing mask. Dust which is injurious to health can be generated when working on wood and other materials. Never use the device to work on any materials containing asbestos!



Caution! Wear safety goggles. Sparks generated during working or splinters, chips and dust emitted by the device can cause loss of sight.

The reprinting or reproduction by any other means, in whole or in part, of documentation and papers accompanying products is permitted only with the express consent of the iSC GmbH.

Subject to technical changes

Items supplied

Please check that the article is complete as specified in the scope of delivery. If parts are missing, please contact our service center or the sales outlet where you made your purchase at the latest within 5 working days after purchasing the product and upon presentation of a valid bill of purchase. Also, refer to the warranty table in the service information at the end of the operating instructions.

- Open the packaging and take out the equipment with care.
- Remove the packaging material and any packaging and/or transportation braces (if available).
- Check to see if all items are supplied.
- Inspect the equipment and accessories for transport damage.
- If possible, please keep the packaging until the end of the guarantee period.

Danger!

The equipment and packaging material are not toys. Do not let children play with plastic bags, foils or small parts. There is a danger of swallowing or suffocating!

Proper use

The Cement Mixer has been designed to mix building materials such as, mortar, adhesive, plaster and similar substances. The relevant mixing action (which depends on the consistency of the materials and the quantity that has to be mixed) must be set up for the appropriate mixing tool.

The equipment is to be used only for its prescribed purpose. Any other use is deemed to be a case of misuse. The user / operator and not the manufacturer will be liable for any damage or injuries of any kind caused as a result of this.

Please note that our equipment has not been designed for use in commercial, trade or industrial applications. Our warranty will be voided if the machine is used in commercial, trade or industrial businesses or for equivalent purposes.

Technical data

Mains voltage:	230V ~ 50Hz
Motor:	550W
Gross drum volume:	125 Litres
Drum mouth opening:	375mm
No load speed:	2950/min
Drum speed:	34/min
Unmixed dry volume:	100 Litres
Mixed wet volume:	91 Litres
Protection class:	II/回
Degree of protection:	IP44

Sound and vibration

Sound and vibration values were measured in accordance with EN ISO 11688.

L _{n4} sound pressure level	79 dB(A)
K uncertainty	3 dE
L _{wa} sound power level	96 dB(A)
K _{wa} uncertainty	3 dB

Wear ear-muffs.

The impact of noise can cause damage to hearing. Total vibration values (vector sum of three directions) determined in accordance with EN ISO 11688.

Keep the noise emissions and vibrations to a minimum.

- Only use appliances which are in perfect working order.
- Service and clean the appliance regularly.
- Adapt your working style to suit the appliance.
- Do not overload the appliance.
- Have the appliance serviced whenever necessary.
- Switch the appliance off when it is not in use.
- Wear protective gloves.

Caution!

Residual risks

Even if you use this electric power tool in accordance with instructions, certain residual risks cannot be rules out. The following hazards may arise in connection with the equipment's construction and layout:

- Lung damage if no suitable protective dust mask is used.
- Damage to hearing if no suitable ear protection is used.
- Health damage caused by hand-arm vibrations if the equipment is used over a prolonged period or is not properly guided and maintained.



For EU countries only

Never place any electric power tools in your household refuse.

To comply with European Directive 2012/19/EC concerning old electric and electronic equipment and its implementation in national laws, old electric power tools have to be separated from other waste and disposed of in an environment-friendly fashion, e.g. by taking to a recycling depot.

Recycling alternative to the return request:
As an alternative to returning the equipment to the manufacturer, the owner of the electrical equipment must make sure that the equipment is properly disposed of if he no longer wants to keep the equipment. The old equipment can be returned to a suitable collection point that will dispose of the equipment in accordance with the national recycling and waste disposal regulations. This does not apply to any accessories or aids without electrical components supplied with the old equipment.