



Einhell



Booster Cable

BT-BO 16/1 A

Item No.: 2030335

Ident No.: 11046

Bar Code: 4006825561548

The BT-BO 16/1 A jumper cable provides very good service to even the inexperienced when helping out with bridging or jump starting petrol engines. It is equipped with 4 fully insulated pole clamps. The conductive material is made of 19.4 mm² aluminium (= 16 mm² copper cable). Delivered in a practical carrying bag, the jumper cable is compliant with DIN 72553-16.

Features & Benefits

- Jumper cables tested according to DIN 72553-16
- 4 all-insulated pole-pliers
- Conductive material made of 19,4 mm² alu (= 16 mm² copper cable)
- Incl. carrying bag



Technical Data

- | | |
|---------------------------------|----------------------|
| - For petrol engines up to max. | 2500 cm ³ |
| - Cable length | 3 m |
| - Cable cross section | 19.4 mm ² |
| - Testing current | 220 A |

Logistic Data

- | | |
|--------------------------------------|----------------------|
| - Product weight | 1.15 kg |
| - Gross weight single packaging | 1.28 kg |
| - Dimensions single packaging | 285 x 285 x 55 mm |
| - Pieces per export carton | 6 Pieces |
| - Gross weight export carton | 8.3 kg |
| - Dimensions export carton | 560 x 280 x 175 mm |
| - Container quantity (20"/40"/40"HC) | 6012 12462 14868 |

